

Atecpool Pool Controls Control Panel

Atecpool Control Panel

Atecpool Control Boxes have IP66 protection rating, made in ABS and glass panel. Control panel box for connection to all electrical pool equipment like pumps, heat pumps, lighting, dosing system, pool covers etc. Monophase or triphase with or without transformer.



Power Box Without Transformer Specification

Power Box for circuit control, timer, dosing, filtration, lighting, pump manual or auto switch

- Housing L265xA300xP120 mm in ABS IP65 gray color with window and transparent cover.
- General cut by residual current device 30ma.
- Command circuit protected by circuit breaker (6A).
- Output for water treatment device with protection by circuit breaker 10A.
- Output for sockets (General Uses) protection by circuit breaker 16A.
- Time switch with power reserve.

	Voltage	Model	Code	Current	Pump		Transformer
	V			(A)	kw	HP	
Monophase	230V AC	QPM	QPM-4	2.5-4A	0.25	0.33	No
					0.37	0.5	
	230V AC	QPM	QPM-6	4-6.3A	0.55	0.75	No
					0.75	1	
230V AC	QPM	QPM-10	6.3-10A	1.1	1.5	No	
					1.5	2	

	Voltage	Model	Code	Current	Pump		Transformer
	V			(A)	kw	HP	
Triphase	400V AC	QPT	QPM-2T	1-1.6A	0.55	0.75	No
	400V AC	QPT	QPM-3T	1.6-2.5A	0.75	1	No
	400V AC	QPT	QPM-4T	2.5-4A	1.1	1.5	No
					1.5	2	
	400V AC	QPT	QPM-7T	4-6.3A	2.2	3	No
				3	4		



Power Box With Transformer Specification

Power Box for circuit control, timer, dosing, filtration, lighting, pump manual or auto switch, projector ON-OFF switch, electricity plug, light.

- Housing L265xA300xP120 mm in ABS IP65 gray color with window and transparent cover.
- Command circuit protected by circuit breaker (6A).
- Output for water treatment device with protection by circuit breaker 10A.
- Output for underwater projectors with protection by circuit breaker 10A.
- Output for Lighting (General Uses) protection by circuit breaker 10A. *
- Output for sockets (General Uses) protection by circuit breaker 16A. *
- Time switch with power reserve.
- Adjustable motor circuit breaker.

	Voltage	Model	Code	Current	Pump		Transformer
				(A)	kw	HP	
Monophase	230V AC	QPM80	QPM80-4	2.5-4A	0.25	0.33	80VA
					0.37	0.5	
	230V AC	QPM80	QPM80-6	4-6.3A	0.55	0.75	80VA
					0.75	1	
230V AC	QPM80	QPM80-10	6.3-10A	1.1	1.5	80VA	
					1.5	2	

	Voltage	Model	Code	Current	Pump		Transformer
				(A)	kw	HP	
Triphase	400V AC	QPT80	QPT80-2T	1 - 1.6A	0.55	0.75	80VA
	400V AC	QPT80	QPT80-3T	1.6-2.5A	0.75	1	80VA
	400V AC	QPT80	QPT80-4T	2.5-4A	1.1	1.5	80VA
					1.5	2	
	400V AC	QPT80	QPT80-7T	4 - 6.3A	2.2	3	80VA
				3	4		